

Colorimetric data for system lines TLS70 -> ORS18, TLS00, NRS18, SRS18

For input LCH^*_{a0} (TLS70) and output LCH^*_{am} for 4 systems ($m = 0$ to 4)
Six CIELAB hue angles of device ORS18: (37.7 96.4 150.9 236.0 305.0 353.7);
Six CIELAB hue angles of device TLS00: (40.0 102.8 136.0 196.4 306.3 328.2);
Six CIELAB hue angles of device NRS18: (25.5 92.3 162.2 217.0 271.7 328.6);
Six CIELAB hue angles of device SRS18: (30.0 90.0 150.0 210.0 270.0 330.0);

no. Colour	->TLS70 LCH^*_{a0}	->TLS70 n^*, c^*, H^*_{ai0}	ORS18 LCH^*_{a1}	TLS00 LCH^*_{a2}	NRS18 LCH^*_{a3}	SRS18 LCH^*_{a4}
01 O=000y	78.2 14.1 22	0.3 0.5 22	48.5 35.3 22	45.2 47.2 22	52.8 37.5 22	52.8 36.1 22
02 o10y	79.0 12.6 30	0.3 0.5 30	48.5 36.2 30	44.8 50.0 30	52.8 36.9 30	52.8 38.7 30
03 o20y	80.0 11.5 39	0.3 0.5 39	48.9 40.8 39	44.4 54.8 39	52.8 34.4 39	52.8 35.9 39
04 o30y	80.9 10.9 48	0.3 0.5 48	52.2 38.1 48	47.0 46.7 48	52.8 32.9 48	52.8 34.3 48
05 o40y	81.7 10.5 56	0.3 0.5 56	55.1 36.7 56	49.7 44.4 56	52.8 32.3 56	52.8 33.6 56
06 o50y	82.6 10.4 65	0.3 0.5 65	58.3 36.0 65	52.7 43.1 65	52.8 32.5 65	52.8 33.6 65
07 o60y	83.4 10.5 73	0.3 0.5 73	61.2 36.2 73	55.4 42.9 73	52.8 33.3 73	52.8 34.4 73
08 o070y	84.4 10.9 82	0.3 0.5 82	64.5 37.3 82	58.4 43.6 82	52.8 35.1 82	52.8 36.1 82
09 o80y	85.2 11.5 90	0.3 0.5 90	67.4 39.1 90	61.1 45.2 90	52.8 37.7 90	52.8 38.7 90
10 o90y	86.1 12.6 99	0.3 0.5 99	68.7 45.1 99	64.1 48.3 99	52.8 36.0 99	52.8 35.9 99
11 Y=y00l	86.9 14.1 107	0.3 0.5 107	65.8 42.8 107	64.8 45.7 107	52.8 33.8 107	52.8 34.4 107

Goal: Transfer coordinates LCH^*_{a0} (system m=0) to LCH^*_{am} (system m=1 to 4)

The given data LCH^*_{a0} include the device hue H^*_{a0}

Integer (i) device hue: $H^*_{ai0} = \text{round} (H^*_{a0})$ (1)

Fetch device data $LCH^*_{a,M0}$ from table with 361 entries for H^*_{ai0} from 0 to 360 degrees

Lightness, chroma, hue: $LCH^*_{a,M0} = LCH^*_{a,M0} [H^*_{ai0}]$ (2)

Calculate lcw^* data from LC^*_{a0} and $LC^*_{a,M0}$:

Relative lightness: $l^* = [L^*_{a0} - L^*_{N0}] / [L^*_{W0} - L^*_{N0}]$ (3)

Relative chroma: $c^* = C^*_{a0} / C^*_{a,M0}$ (4)

Relative Blackness: $n^* = 1 - l^* + c^* [L^*_{M0} - L^*_{N0}] / [L^*_{W0} - L^*_{N0}]$ (5)

Fetch device data $LCH^*_{a,Mm}$ from table with 361 entries for H^*_{ai0} from 0 to 360 degrees

lightness, chroma, hue: $LCH^*_{a,Mm} = LCH^*_{a,Mm} [H^*_{ai0}]$ (6)

For any input or output device (m=0 to 4) it is valid for constant n^*, c^*, l^*, H^*_{a*} :

CIELAB lightness: $L^*_m = L^*_{am} = L^*_{Nm} + l^* [L^*_{Wm} - L^*_{Nm}]$ (7)

Adated CIELAB chroma: $C^*_{am} = c^* C^*_{a,Mm}$ (8)

Adated CIELAB hue: $H^*_{am} = H^*_{a0}$ (9)

Result: device dependent adapted CIELAB data of 4 systems m=1 to 4:

lightness, chroma, hue: LCH^*_{am} (10)

Colorimetric data for system lines TLS70 -> ORS18, TLS00, NRS18, SRS18

For input olv^*_{30} (TLS70) and output LCH^*_{am} for 4 systems ($m = 0$ to 4)
Six CIELAB hue angles of device ORS18: (37.7 96.4 150.9 236.0 305.0 353.7);
Six CIELAB hue angles of device TLS00: (40.0 102.8 136.0 196.4 306.3 328.2);
Six CIELAB hue angles of device NRS18: (25.5 92.3 162.2 217.0 271.7 328.6);
Six CIELAB hue angles of device SRS18: (30.0 90.0 150.0 210.0 270.0 330.0);

no. Colour	->TLS70 olv^*_{30}	->TLS70 n^*, c^*, H^*_{si0}	ORS18 LCH^*_{a1}	TLS00 LCH^*_{a2}	NRS18 LCH^*_{a3}	SRS18 LCH^*_{a4}
01 O=000y	0.7 0.2 0.2 0.3 0.5 30		48.5 35.3 22	45.2 47.2 22	52.8 37.5 22	52.8 36.1 22
02 o10y	0.7 0.25 0.2 0.3 0.5 35		48.5 36.2 30	44.8 50.0 30	52.8 36.9 30	52.8 38.7 30
03 o20y	0.7 0.3 0.2 0.3 0.5 41		48.9 40.8 39	44.4 54.8 39	52.8 34.4 39	52.8 35.9 39
04 o30y	0.7 0.35 0.2 0.3 0.5 47		52.2 38.1 48	47.0 46.7 48	52.8 32.9 48	52.8 34.3 48
05 o40y	0.7 0.4 0.2 0.3 0.5 53		55.1 36.7 56	49.7 44.4 56	52.8 32.3 56	52.8 33.6 56
06 o50y	0.7 0.45 0.2 0.3 0.5 60		58.3 36.0 65	52.7 43.1 65	52.8 32.5 65	52.8 33.6 65
07 o60y	0.7 0.5 0.2 0.3 0.5 66		61.2 36.2 73	55.4 42.9 73	52.8 33.3 73	52.8 34.4 73
08 o070y	0.7 0.55 0.2 0.3 0.5 73		64.5 37.3 82	58.4 43.6 82	52.8 35.1 82	52.8 36.1 82
09 o80y	0.7 0.6 0.2 0.3 0.5 79		67.4 39.1 90	61.1 45.2 90	52.8 37.7 90	52.8 38.7 90
10 o90y	0.7 0.65 0.2 0.3 0.5 85		68.7 45.1 99	64.1 48.3 99	52.8 36.0 99	52.8 35.9 99
11 Y=y00l	0.7 0.7 0.2 0.3 0.5 90		65.8 42.8 107	64.8 45.7 107	52.8 33.8 107	52.8 34.4 107

Goal: Transfer coordinates olv^*_{30} (system m=0) to LCH^*_{am} (system m=1 to 4)

The following equations for relative blackness and chroma are valid for any device:

$$n^* = 1 - \max (o^*_{30}, l^*_{30}, v^*_{30}) \quad (1)$$

$$c^* = \max (o^*_{30}, l^*_{30}, v^*_{30}) - \min (o^*_{30}, l^*_{30}, v^*_{30}) \quad (2)$$

For the calculation of the missing relative device hue assume

as a starting point that the three values olv^*_{30} belong to the standard (s) device SRS18:

relative red-green chroma: $a^*_{r0} = o^*_{30} \cos(30) + l^*_{30} \cos(150)$ (3)

relative yellow-blue chroma: $b^*_{r0} = o^*_{30} \sin(30) + l^*_{30} \sin(150) - v^*_{30} \sin(270)$ (4)

Standard integer hue: $H^*_{si0} = \text{round} [\text{atan} (b^*_{r0} / a^*_{r0})]$ (5)

Fetch device integer hue: $H^*_{ai0} = H^*_{si-ai} [H^*_{si0}]$ (6)

Fetch device data $LCH^*_{a,M0}$ from table with 361 entries for H^*_{ai0} from 0 to 360 degrees

Lightness, chroma, hue: $LCH^*_{a,M0} = LCH^*_{a,M0} [H^*_{ai0}]$ (7)

Fetch device data $LCH^*_{a,Mm}$ from table with 361 entries for H^*_{ai0} from 0 to 360 degrees

lightness, chroma, hue: $LCH^*_{a,Mm} = LCH^*_{a,Mm} [H^*_{ai0}]$ (8)

For any input or output device (m=0 to 4) it is valid for constant n^*, c^*, l^*, H^*_{a*} :

CIELAB lightness: $L^*_m = L^*_{am} = L^*_{Nm} + l^* [L^*_{Wm} - L^*_{Nm}]$ (9)

Adated CIELAB chroma: $C^*_{am} = c^* C^*_{a,Mm}$ (10)

Adated CIELAB hue: $H^*_{am} = H^*_{a,M0} = H^*_{a,Mm}$ (11)

Result: device dependent adapted CIELAB data of 4 systems m=1 to 4:

lightness, chroma, hue: LCH^*_{am} (12)