

Interpretation *rgb* $\rightarrow$ *olv**- und CIELAB-Daten

sRGB-Display mit der Leuchtdichte-Reflexion $L_r=0\%$

Buntonkreis mit 6 Geräte-Bunttönen *OYLCVM*:

$h_{ab,a} = 40.0, 102.8, 136.0, 196.3, 306.2, 328.2$

Elementar-Bunttöne *RJGB*: $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$

<i>Code</i>	L^*	a^*_a	b^*_a	C^*_{ab}	$h_{ab,a}$	<i>rgb</i> $\rightarrow$ <i>olv</i> *
<i>o00y=O</i>	50.4	76.9	64.5	100.4	40.0	1.00 0.00 0.00
<i>o12y</i>	51.5	73.9	64.9	98.3	41.3	1.00 0.12 0.00
<i>o25y</i>	54.0	66.7	65.9	93.8	44.6	1.00 0.25 0.00
<i>o37y</i>	58.2	55.4	67.9	87.7	50.7	1.00 0.37 0.00
<i>o50y</i>	63.6	41.3	71.0	82.2	59.7	1.00 0.50 0.00
<i>o62y</i>	70.1	25.7	75.0	79.3	71.0	1.00 0.62 0.00
<i>o75y</i>	77.2	9.8	79.7	80.4	82.9	1.00 0.75 0.00
<i>o87y</i>	84.8	-5.7	85.0	85.2	93.8	1.00 0.87 0.00