

Interpretation *rgb* \rightarrow *olv**- und CIELAB-Daten

sRGB-Display mit der Leuchtdichte-Reflexion $L_r=20\%$

Buntonkreis mit 6 Geräte-Bunttönen *OYLCVM*:

$h_{ab,a} = 24.9, 105.5, 140.4, 197.1, 297.2, 327.0$

Elementar-Bunttöne *RJGB*: $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$

<i>Code</i>	L^*	a^*_a	b^*_a	C^*_{ab}	$h_{ab,a}$	<i>rgb</i> \rightarrow <i>olv*</i>
<i>o00y=O</i>	65.5	45.0	20.9	49.7	24.9	1.00 0.00 0.00
<i>o12y</i>	66.0	43.6	21.7	48.7	26.4	1.00 0.12 0.00
<i>o25y</i>	67.4	40.3	23.5	46.6	30.3	1.00 0.25 0.00
<i>o37y</i>	69.7	34.6	26.6	43.7	37.5	1.00 0.37 0.00
<i>o50y</i>	73.0	26.8	30.9	41.0	49.0	1.00 0.50 0.00
<i>o62y</i>	77.1	17.4	36.3	40.3	64.3	1.00 0.62 0.00
<i>o75y</i>	81.9	6.9	42.4	43.0	80.7	1.00 0.75 0.00
<i>o87y</i>	87.4	-4.2	49.1	49.3	94.9	1.00 0.87 0.00

R

J